

Luxul Xen™ XMS-1008P Firmware Update Instructions:

1. Download the appropriate firmware file for the XMS-1008P from <http://luxul.com/firmware> and save it to your computer.



WARNING! Do not upgrade the firmware over a wireless connection or the unit may become damaged.



WARNING! Do not power off the router or the computer connected to it during the upgrade process or the unit may become damaged.

2. Using a web browser, type the IP address of your XMS-1008P (192.168.0.3) to access the management interface.


3. Login to the interface. Default user name: **admin**; Default password: **admin**


4. In the left navigation of the interface select
System >> Firmware Upgrade

Use the **Browse** button to find the file on your computer and click **Open** then **Upgrade**




5. Once the upgrade process starts you will see a progress bar. Once finished, you will be asked if you want to activate the new firmware, choose **Yes**






- After selecting **Yes** you will receive a message that the "Firmware upgrade is complete." Click **OK** and the switch will automatically reboot with the new firmware.



- Log back into the XMS-1008P interface
- Click on **Status** to check the Firmware Version on the XMS-1008P (it should be V1.0.1.2)



9. Now, check to see if POE is enabled. To enable POE, the **PoE Enabled** checkbox for each port should be checked, and the **Power Management Mode** should be set to **Dynamic Allocation**. You can enable these settings manually or you can restore the unit to factory defaults.

PoE (Power over Ethernet) Configuration

Power Management Mode: PO Based Priority Static Allocation Dynamic Allocation

Power Utilization: 0% 0 W / 120 W

PSE Temperature: 27.0

Port	PoE Enabled	Delivering Power [W]	Voltage [V]	Current [mA]	Priority	Stat
1	<input checked="" type="checkbox"/>	0	0	0	Low	
2	<input checked="" type="checkbox"/>	0	0	0	Low	
3	<input checked="" type="checkbox"/>	0	0	0	Low	
4	<input checked="" type="checkbox"/>	0	0	0	Low	
5	<input checked="" type="checkbox"/>	0	0	0	Low	
6	<input checked="" type="checkbox"/>	0	0	0	Low	
7	<input checked="" type="checkbox"/>	0	0	0	Low	
8	<input checked="" type="checkbox"/>	0	0	0	Low	

10. To Restore the XMS-1008P to factory defaults select **System >> Factory Restore**. Click **Apply** to restore the factory defaults. The switch will reboot and POE will now be enabled on all ports.

Restore Factory Defaults

Press Apply to restore to factory defaults.

[Apply](#)